



According to ISO 1179-2

| Part n°        | R1                 | L1  | ØA   | ØB   |
|----------------|--------------------|-----|------|------|
| <b>JVBSP02</b> | 1/8" BSP - M10x1   | 1   | 11.9 | 8.4  |
| <b>JVM12</b>   | M12x1.5            | 1,5 | 14.4 | 9.8  |
| <b>JVBSP04</b> | 1/4" BSP - M14x1.5 | 1,5 | 16.5 | 11.6 |
| <b>JVM16</b>   | M16x1.5            | 1,5 | 18.9 | 13.8 |
| <b>JVBSP06</b> | 3/8" BSP           | 1,5 | 18.9 | 14.7 |
| <b>JVM18</b>   | M18x1.5            | 1,5 | 20.9 | 15.7 |
| <b>JVM20</b>   | M20x1.5            | 1,5 | 22.9 | 17.8 |
| <b>JVBSP08</b> | 1/2" BSP           | 1,5 | 23.9 | 18.5 |
| <b>JVM22</b>   | M22x1.5            | 1,5 | 24.3 | 19.6 |
| <b>JVBSP12</b> | 3/4" BSP - M26x1.5 | 1,5 | 29.2 | 23.9 |
| <b>JVBSP16</b> | 1" BSP - M33x2     | 2   | 35.7 | 29.7 |
| <b>JVBSP20</b> | 1"1/4 BSP - M42x2  | 2   | 45.8 | 38.8 |
| <b>JVBSP24</b> | 1"1/2 BSP - M48x2  | 2   | 50.7 | 44.7 |
| <b>JVBSP32</b> | 2" BSP             | 4   | 67   | 56,3 |